

# Contactors Specification and Selection Guide

Model	New Nomenclature Model	230 volt - 1 contactor			230 volt - 2 contactors			460 volt - 1 contactor			460 volt - 2 contactor		
		Part Number		Amp	Part Number		Amp	Part Number		Amp	Part Number		Amp
		110V Coil	230V Coil		110V Coil	230V Coil		110V Coil	230V Coil		110V Coil	230V Coil	
4DA3-100E-TSK	4DA3R12ME-TSK	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
4DA3-101E-TSK	4DA3F47KE-TSK	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
4DE3-100E-TSK	4DE3R12ME-TSK	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
4DA3-200E-TSK	4DE3R18ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DA3-2000-FSD	4DE3R18M0-FSD							912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4DA3-2000-TSK	4DE3R18M0-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DA4-2000-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DE3-200E-TSK	4DE3R18ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DE3-2000-FSD	4DE3R18M0-FSD							912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4DE3-2000-FSD	4DE3R18M0-FSD	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DB3-2200-TSK	4DB3R20M0-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DC3-2200-TSK	4DC3R20M0-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DH3-150E-TSK	4DH3R16ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DH3-250E-TSK	4DK3R22ME-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DH3-2500-TSK	4DK3R22M0-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DJ3-3000-TSK	4DJ3R28M0-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DK3-150E-TSK	4DK3R16ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DK3-250E-TSK	4DK3R22ME-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DK3-2500-FSD	4DK3R22M0-FSD							912-3050-01	912-3050-02	50	912-3030-01	912-3030-02	2-30
4DK3-2500-TSK	4DK3R22M0-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DL3-150E-TSK	4DL3F63KE-TSK	912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DN3-101E-TSK	4DN3F47KE-TSK	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
4DP3-150E-TSK	4DP3F63KE-TSK	912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DP8-150E-TSK	4DP8F63KE-TSK	912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DR3-200E-TSK	4DR3R19ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DR3-300E-TSK	4DR3R28ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DR3-3000-FSD	4DR3R28M0-FSD							912-3050-01	912-3050-02	50	912-3030-01	912-3030-02	2-30
4DR3-3000-TSK	4DR3R28M0-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4DS3-220E-TSK	4DS3F76KE-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4DT3-220E-FSD	4DT3F76KE-TSK							912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4DT3-220E-TSK	4DT3F76KE-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4RA3-100A-TSK		912-3060-01	912-3060-02	60	912-3030-01	912-3030-02	2-30	912-3030-01	912-3030-02	30			
4RA3-200A-TSK		912-3075-01	912-3075-02	75	912-3050-01	912-3050-02	2-50	912-3040-01	912-3040-02	40			
4RA4-200A-TSK		912-3075-01	912-3075-02	75	912-3050-01	912-3050-02	2-50	912-3040-01	912-3040-02	40			
4RE2-200A-FSD								912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4RE2-200A-TSK		912-3075-01	912-3075-02	75	912-3050-01	912-3050-02	2-50	912-3040-01	912-3040-02	40			
4RH1-150A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4RJ1-300A-FSD								912-3060-01	912-3060-02	60	912-3030-01	912-3030-02	2-30
4RK2-250A-FSD								912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25
4RK2-250A-TSK		912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
4RL1-150A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4RL2-150A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
4RR1-300A-FSD								912-3060-01	912-3060-02	60	912-3030-01	912-3030-02	2-30
4RR1-300A-TSK		912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
4RR2-300A-TSK		912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6DB3-3000-TSK	6DB3R32M0-TSK	912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6DC3-270E-TSK	6DC3F93KE-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DD3-270E-TSK	6DD3F93KE-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DE3-300E-TSK	6DE3F11ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DF3-300E-TSK	6DF3F11ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DG3-350E-TSN	6DN3R37ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			

## Contactor Specification and Selection Guide

6DG3-3500-FSD	6DG3R37M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DG3-3500-TSN	6DG3R37M0-TSK	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DH3-200E-TSK	6DH3R23ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6DH3-350E-TSK	6DP3R35ME-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DH3-3500-FSD	6DP3R35M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DH3-3500-TSK	6DP3R35M0-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DJ3-300E-TSK	6DS3R28ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DJ3-400E-TSN	6DS3R40ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DJ3-4000-TSN	6DS3R40M0-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DK3-200E-TSK	6DK3R23ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6DK3-350E-TSK	6DP3R35ME-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DK3-3500-FSD	6DP3R35M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DK3-3500-TSK	6DP3R35M0-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DL3-270E-TSK	6DL3F93KE-TSK	912-3090-01	912-3090-02	90	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DM3-3500-FSD	6DN3R37M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DM3-3500-TSN	6DN3R37M0-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DN3-350E-TSN	6DN3R37ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DN3-3500-FSD	6DN3R37M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DN3-3500-TSN	6DN3R37M0-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DP3-200E-TSK	6DP3R23ME-TSK	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6DP3-350E-FSD	6DP3R35ME-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DP3-350E-TSK	6DP3R35ME-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DP3-3500-FSD	6DP3R35M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DP3-3500-TSK	6DP3R35M0-TSK	912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DR3-300E-TSK	6DR3R26ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DR3-400E-FSD	6DS3R40ME-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DR3-400E-TSN	6DS3R40ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DR3-4000-FSD	6DS3R40M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DR3-4000-TSN	6DS3R40ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DS3-300E-TSK	6DS3R28ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DS3-400E-TSN	6DS3R40ME-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DS3-4000-FSD	6DS3R40M0-FSD							912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6DS3-4000-TSN	6DS3R40M0-TSN	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6DT3-300E-FSD	6DT3F11ME-FSD							912-3050-01	912-3050-02	50	912-3030-01	912-3030-02	2-30
6DT3-300E-TSK	6DT3F11ME-TSK	912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6DW3-3000-FSD	6DY3R32M0-FSD							912-3050-01	912-3050-02	50	912-3040-01	912-3040-02	2-40
6DW3-3000-TSK	6DY3R32M0-TSK	912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6DY3-3000-FSD	6DY3R32M0-FSD							912-3050-01	912-3050-02	50	912-3040-01	912-3040-02	2-40
6DY3-3000-TSK	6DY3R32M0-TSK	912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6RA4-100A-TSK		912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
6RA4-200A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6RB2-100A-TSK		912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	2-25	912-3025-01	912-3025-02	25			
6RB2-200A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6RE2-200A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6RH1-200A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6RL1-250A-TSK		912-3120-01	912-3120-02	120	912-3050-01	912-3050-02	2-50	912-3050-01	912-3050-02	50			
6RN2-300A-TSK		912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6RP2-200A-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
6RP2-350A-FSD								912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6RP2-350A-TSK		912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6RS2-400A-FSD								912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40
6RS2-400A-TSN		912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75	912-3075-01	912-3075-02	75			
6RT1-300A-TSK		912-3120-01	912-3120-02	120	912-3060-01	912-3060-02	2-60	912-3060-01	912-3060-02	60			
6TM1-2000-TSK		912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	2-40	912-3040-01	912-3040-02	40			
8DP1-5000-FSD	8DP1R56M0-FSD							912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75
8DP1-5000-TSK	8DP1R56M0-TSK	912-3200-01	912-3200-02	200	912-3120-01	912-3120-02	2-120	912-3120-01	912-3120-02	120			
8DS1-6000-FSD	8DS1R67M0-FSD							912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75
8DS1-6000-TSK	8DS1R67M0-TSK				912-3120-01	912-3120-02	2-120	912-3120-01	912-3120-02	120			

## Contactor Specification and Selection Guide

Model	New Nomenclature Model	200 volt - 1 contactor			200 volt - 2 contactors		
		Part Number		Amp Rating	Part Number		Amp Rating
		110V Coil	230V Coil		110V Coil	230V Coil	
6DG3*3500-FSU	6DG3R37MO-FSU	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75
6DM3*3500-FSU	6DM3R37MO-FSU	912-3200-01	912-3200-02	200	012-3075-01	912-3075-02	2-75
6DN3*350E-FSU	6DN3R37ME-FSU	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75
6DN3*3500-FSU	6DN3R37MO-FSU	912-3200-01	912-3200-02	200	912-3075-01	912-3075-02	2-75
6DS3*4000-FSU	6DS3R40M0FSU	912-3200-01	912-3200-02	200	912-3090-01	912-3090-02	2-90
6RS2-400A-FSU					912-3090-01	012-3090-02	2-90

Model	New Nomenclature Model	575 volt - 1 contactor			575 volt - 2 contactors		
		Part Number		Amp Rating	Part Number		Amp Rating
		110V Coil	230V Coil		110V Coil	230V Coil	
4DA3-2000-TSE	4DA3R18M0-TSE	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4DC3-2200-TSE	4DC3R20M0-TSE	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
4DK3-2500-TSE	4DK3R22M0-TSE	912-3050-01	912-3050-02	50	912-3030-01	912-3030-02	2-30
4DR3-3000-TSE	4DR3R28M0-TSE	912-3050-01	912-3050-02	50	912-3040-01	912-3040-02	2-40
4RK2-250A-TSE		912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	2-25
6DG3-3500-TSE		912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40
6DH3-3500-TSE		912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40
6DN3-3500-TSE		912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40
6DP3-3500-TSE		912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40
6DS1-4000-TSE		912-3060-01	912-3060-02	60	912-3040-01	912-3040-02	2-40
8DP1-5000-TSE		912-3120-01	912-3120-02	120	912-3075-01	912-3075-02	2-75

RLA - Rated load amps.

LRA - The current drawn by a motor which is "locked" and cannot rotate. It occurs instantly during start up.

\* "A" in this position, delta reed model, "dash" in this position, floating reed model.

## Replacement Coil Information

Coil Voltage	Coil Part Number	Amp Rating of Contactor
24	923-0002-00	50-75
104/120	923-0002-01	50-75
208/240	923-0002-02	50-75
440/480	923-0002-03	50-75

## Three Phase Compressors General 3 Pole Contactor Requirements

Model	230 volt - 1 contactor			460 Volt - 1 contactor		
	Part Number		Amp Rating	Part Number		Amp Rating
	110V Coil	230V Coil		110V Coil	230V Coil	
K -Body Compressor	912-3015-01	912-3015-02	15	912-3015-01	912-3015-02	15
L -Body Compressor	912-3015-01	912-3015-02	15	912-3015-01	912-3015-02	15
E -Body Compressor	912-3015-01	912-3015-02	15	912-3015-01	912-3015-02	15
3R Body Compressor	912-3025-01	912-3025-02	25	912-3015-01	912-3015-02	15
NR Body Compressor	912-3025-01	912-3025-02	25	912-3015-01	912-3015-02	15
MR Body Compressor	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	25
9R 15 hp	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	40
9R 10 hp	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	25
9R 5 & 7.5 hp	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	25
2D Body Compressor	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	25
3D 5 & 6 hp	912-3040-01	912-3040-02	40	912-3025-01	912-3025-02	25
3D 7.5 & 10 hp	912-3050-01	912-3050-02	50	912-3025-01	912-3025-02	25
3D 12 hp	912-3060-01	912-3060-02	60	912-3030-01	912-3030-02	30
3D 15 hp	912-3075-01	912-3075-02	75	912-3040-01	912-3040-02	40

## Auxiliary Contact Information

**For use with 912-3015-\_\_ through 912-3075-\_\_ 3 pole 15-75 Amp  
Definite Purpose Contactors only**

Description	Part Number	Terminal Capacity
1NO	912-0001-10	Range: (2) 12-14 AWG Stranded or Solid or (2) 16 AWG Stranded Only. Torque: 7 lb-in. Use Copper Wire Only
1NC	912-0001-11	
1NO/1NC	912-0001-12	
2NO	912-0001-13	
2NC	912-0001-14	

**For use with 912-3090-\_\_ 3 pole 90 Amp  
Definite Purpose Contactors only**

Description	Part Number	Terminal Capacity
1NO	912-0001-15	Max: (1) 12 AWG Torque: 6-9 lb-in. Use Copper Wire Only
1NC	912-0001-16	
1NO/1NC	912-0001-17	
2NC	912-0001-18	

**For use with 912-3120-\_\_ through 912-3360-\_\_ 3 pole 120-360 Amp  
Definite Purpose Contactors only**

Description	Part Number	Terminal Capacity
1NO	912-0001-19	Range: (2) 12-14 AWG Stranded or Solid or (2) 16 AWG Stranded Only. Torque: 7 lb-in. Use Copper Wire Only
1NC	912-0001-20	
1NO/1NC	912-0001-21	

### 912-0001-22 Mechanical Interlock Assembly

For use with 912-3015-\_\_ through 912-3075-\_\_ 3 Pole 15-75 Amp Definite Purpose Contactors

## Auxiliary Contact Location

■ Contactor Part Number	Size	Pole	Available Mounting Position	Max. # of Aux. Contacts	Max. # of Circuits	Figure
912-30**-__	15-75 Amp	3	L1, R1	2	4	1
912-3090-__	90 Amp	3	L1, R1	2	4	1
912-3120-__	120 Amp	3	L1, L2, L3, R2, R3 ●	5	10	2
912-3***-__	200-360 Amp	3	L2, L3, R1, R2, R3 ●	5	10	2

■ Underscore ( \_\_ ) indicates missing magnet coil suffix.

\*\* Indicates fields for desired amp rating of device.

● Available position on contactor other than what is factory installed.

